

HƯỚNG DẪN CÀI ĐẶT GỬI CẢNH BÁO QUA GMAIL

I.Cấu hình thông số Gmail

Đăng nhập vào thiết bị
Configuration --- > Network --- > Advanced
settings --- > Email

- 1.Đặt tên kiểu cảnh báo
 - 2.Tài khoản Gmail gửi
 - 3.server SMTP “ smtp.gmail.com”
 - 4.Port SMTP “ 587 “
 - 5.User tài khoản gmail gửi
 - 6.Mật khẩu tài khoản gmail gửi
 - 7.Nhập lại mật khẩu tài khoản gửi
 - 8.Địa chỉ Gmail nhận
- Save lại

The screenshot shows the Configuration page of a security camera interface. The 'Configuration' tab is selected, and the 'Email' sub-tab is active. The settings are as follows:

- Sender: báo động 1
- Sender's Address: sontunghik@gmail.com 2
- SMTP Server: smtp.gmail.com 3
- SMTP Port: 587 4
- Enable SSL:
- Attached Image:
- Interval: 2 s
- Authentication:
- User Name: sontunghik@gmail.com 5
- Password: [Redacted] 6
- Confirm: [Redacted] 7

Below the settings is a 'Receiver' table:

No.	Receiver	Receiver's Address	Test
1	camera	kythuat@lehoangcctv.com 8	Test
2			Test
3			Test

A red 'Save' button is located at the bottom of the configuration page.

II. Cài đặt Báo Động

Configuration --- > Event --- > Basic Event --- > Motion

1. Bật “Enable Motion Detection”

2. Chọn “Draw Area” sử dụng

chuột quét vùng.

Save lại

The screenshot displays the 'Configuration' tab of a security camera system. The left sidebar shows a navigation menu with 'Basic Event' selected. The main panel is titled 'Motion' and includes a dropdown for 'Channel No.' set to 'Analog Camera 1'. A red '1' indicates the first step: 'Enable Motion Detection' is checked. Below this, there are tabs for 'Area Settings', 'Arming Schedule', and 'Linkage Method'. A video feed window shows a room with a red grid overlay. A red '2' indicates the second step: 'Draw Area' is selected. Below the video feed, a 'Sensitivity' slider is set to '3', with a red '3' next to it. A red 'Save' button is at the bottom.

III. Cài đặt Thời gian Báo động.

Tùy chọn đặt thời gian cảnh báo

Save lại

The screenshot shows a web-based configuration interface for a security camera. The top navigation bar includes 'Live View', 'Playback', 'Picture', and 'Configuration' (which is highlighted in red). Under 'Configuration', there are sub-tabs: 'Motion' (selected), 'Video Tampering', 'Video Loss', 'Alarm Input', 'Alarm Output', and 'Exception'. The 'Motion' tab is active, showing settings for 'Analog Camera1'. The 'Channel No.' is set to 'Analog Camera1'. There are two checkboxes: 'Enable Motion Detection' (checked) and 'Enable Dynamic Analysis for Motion' (unchecked). Below these are three tabs: 'Area Settings', 'Arming Schedule' (selected), and 'Linkage Method'. Under 'Arming Schedule', there are 'Delete' and 'Delete All' buttons. The main area displays a 7-day arming schedule grid. Each day (Mon-Sun) has a blue bar indicating that motion detection is armed for the entire 24-hour period. The grid has columns for hours from 0 to 24 in increments of 2.

Day	0	2	4	6	8	10	12	14	16	18	20	22	24
Mon	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed
Tue	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed
Wed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed
Thu	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed
Fri	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed
Sat	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed
Sun	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed	Armed

At the bottom of the configuration page, there is a red 'Save' button.

IV. Kiểu Gửi Cảnh Báo

Chọn “ Send Email ” Gửi cảnh báo qua Email

Audible Warning : âm báo tại đầu ghi

Notify Surveillance Center : gửi cảnh báo qua phần mềm điện thoại

Full screen monitoring : cảnh báo trên màn hình tivi

Upload Pictures to cloud : gửi hình ảnh về server cloud

Save lại

The screenshot shows the Configuration page for a security camera system. The 'Motion' tab is selected, and the 'Linkage Method' sub-tab is active. The 'Channel No.' is set to 'Analog Camera 1'. The 'Enable Motion Detection' checkbox is checked. The 'Linkage Method' table is as follows:

<input type="checkbox"/> Normal Linkage	<input type="checkbox"/> Trigger Alarm Output	<input type="checkbox"/> Trigger Channel
<input type="checkbox"/> Audible Warning	<input type="checkbox"/> A->1	<input checked="" type="checkbox"/> A1
<input checked="" type="checkbox"/> Send Email	<input type="checkbox"/> A->2	<input type="checkbox"/> A2
<input type="checkbox"/> Notify Surveillance Center	<input type="checkbox"/> A->3	<input type="checkbox"/> A3
<input type="checkbox"/> Full Screen Monitoring	<input type="checkbox"/> A->4	<input type="checkbox"/> A4
<input type="checkbox"/> Upload Pictures to Cloud	<input type="checkbox"/> A->5	<input type="checkbox"/> A5
	<input type="checkbox"/> A->6	<input type="checkbox"/> A6
	<input type="checkbox"/> A->7	<input type="checkbox"/> A7
	<input type="checkbox"/> A->8	<input type="checkbox"/> A8
	<input type="checkbox"/> A->9	
	<input type="checkbox"/> A->10	
	<input type="checkbox"/> A->11	
	<input type="checkbox"/> A->12	

A red 'Save' button is located at the bottom of the configuration page.

V.Cài đặt Gmail

Kết nối vào Gmail gửi ,vào liên kết

<https://myaccount.google.com/lesssecureapps>

Bật chế độ kém an toàn

