



HƯỚNG DẪN SỬ DỤNG CAMERA CONSUMER HIKVISION





DS-2CV2U01EFD-IW DS-2CV2U21FD-IW

DS-2CV2Q01EFD-IW DS-2CV2Q21FD-IW

Kết nối và xem camera trên điện thoại



Bước 1



Bước 2





LEHOANG SECURITY CAMERA & ALARM Địa chỉ : 872-872A Tạ Quang Bửu, Phường 5, Quận 8, TP.Hồ Chí Minh - Điện thoại: 028 39812099



Các bước thao tác trên app Hik-Connect



(1) - Chọn: Thêm thiết bị
(2) - Quét mã QR code trên camera
(5) - Quét mã QR code trên camera

(4) – Chọn: Đồng ý
(5) – Chọn: Tiếp theo



Các bước thao tác trên app Hik-Connect



(6) – Đang kết nối wifi

(7) – Reset và làm lại nếu không kết nối wifi
(8) – Chọn: Kết thúc (Đã kết nối vào wifi)

(9) – Chọn: Lưu

(10) – Kết nối thành công

LEHOANG Địa chỉ : 872-872A Tạ Quang Bửu, Phường 5, Quận 8, TP.Hồ Chí Minh - Điện thoại: 028 39812099



Cài đặt các thông số trên camera





Chia sẻ thiết bị



(1) – Chọn chia sẻ

0

(2) – Chọn 1 trong 2 cách
+ Nhập tài khoản cần chia sẻ
+ Hoặc quét mã của tài khoản gốc

(3) – Cách 1: Nhập tài khoản cần chia sẻ
(4) Cích 2: O (4) - Cích 2: Cích 2:

(4) – Cách 2: Quét mã của tài khoản gốc

LEHOANG Địa chỉ : 872-872A Tạ Quang Bửu, Phường 5, Quận 8, TP.Hồ Chí Minh - Điện thoại: 028 39812099

Cấu hình camera qua IVMS 4200 – Remote Configuration



+ Chỉnh ghi hình liê tục 24/24

+ Chỉnh xoay ngược hình ảnh

System	Configuring the Recording Schedule				
Network	Camera: Camera1 v				
orage	Record				
vent					
Motion Detection	Local Recording				
Video Tampering Detection					
 Wideo Loss Email 	Recording Type: Main Stream				
	Recording Schedule: Alarm Template				
Exception	Advanced Settings				
Schedule	Capture Settings				
🚳 CCD 🚳 Image	Capture Settings				
	Snapshot Type: Main Stream				
	Capture Schedule: Custom				
	Advanced Settings				

+ Kết nối wifi cho camera

Remote Configuration x						
🐮 🚳 System	Configuring the WI-FI Settings Configuring the WI-FI Settings WLAN Settings					
🖃 🚳 Network						
🎡 General	Enable	The Wlan Hotspot w	rill be disabled after	the Wi-Fi being enabled.		
🛞 DDNS Chọn wifi	cần kết nối 🛽 s	SID: HIKVISION VIETNA	М		Select	
FTP Settings	Working Me	lode: 🖲 Manage	O Ad-Hoc			
🎡 NAT	Encryption Me	lode: O None	WEP	WPA-PSK WPA2-enterprise		
😫 Wi-Fi	Encryption T	Type: AES		U WPA2-enterprise		
🎡 QoS	Authentication M	lode: 💿 Open	O Shared			
HTTPS	Key Len	ngth: 💿 64bit	128bit	152bit		
Advanced Settings	Key T	Type: 🔘 Hex	ASCII			
💮 Hik-Connect Nhận mậ	t khẩu wifi 🛛 ĸ	(ev 1 🔘				
Storage						
🕐 🗞 Event	к	Key 2 🔘				
🕑 🗞 CCD	к	Key 3 🔘				
🕐 🚳 Image	к	Key 4				

Remote Configuration System 3 Other Settings Network Storage Parameter Event Video Standard: PAL(50HZ) ~ CCD ~ Video Input Mode: Close Day/Night Switch Settings Mirror: Center ~ Wideo Parameters Off White Balance Left-Right Chỉnh xoay ngược hình ảnh Up-Down Exposure Center WDR Day Night Switch Digital Noise Reduction Back Light Compensation) Image

+ Bật âm thanh 2 chiều

Remote Configuration ×						
🖭 🚳 System	Configuring the Image Quality, Resolution and Other Parameters of the Camera					
🕐 🍪 Network	Camera: Camera1 v					
🖭 🌚 Storage	Video Bật âm thanh 2 chiều cho camera					
🕐 🍪 Event	Stream Type: Main Stream					
🕐 🍪 CCD						
🖃 🚳 Image	Stream type: -> Main stream chon Video type:> Video & Audio					
🔅 Video & Audio	Stream type:> Sub stream chon Video type:> Video & Audio					
🎡 Image Settings	Frame Type: P v Frame Rate: 15fps v					
🎡 Video Display	I Frame Interval: 50 Audio Encoding Type: G711_U					
💮 ROI	Video Encoding Type: STD_H264 Video Encoding Co Medium V					
	Smoothing: Clear - Smo					
	File Size Per Day: 5.0G					
	Audio					
	Audio Input Type: Mic In Volume:					
	Environmental Nois Close					
	Copy to Save					

User name: admin

Mật khẩu: adminXXXXXX

XXXXXX: là 6 ký tự Verification Code được in dưới tem của camera





HƯỚNG DẪN SỬ DỤNG CAMERA CONSUMER HIKVISION

